

## Chico X

SPOTLIGHT 

Product Name | Chico X  
30W



Class II  
AC220-240V

IP Rating  
54

Material  
Aluminium

Install Person/s  
1x 



**CAUTION – This product must be installed by a qualified installer**

Please read instruction manual carefully before installing luminaire



**Surge Protection**

For comprehensive protection of a luminaire against electrical surges, surge protection shall be installed on the mains supply where required to protect luminaires and drivers from transient voltage damage.



**For warranty information visit <https://arrco.ae/terms-of-sale/>**







Please read these installation instructions carefully before installing this product. This product must be installed and maintained by a suitably qualified person/s in compliance with the latest applicable regulations and relevant legislation. SYW does not warrant any claim based on defects or damage caused by misuse, improper installation, improper operation and/or modifications carried out by the purchaser or third parties. This product shall not be used as a 'working light' during construction. This will result in the warranty of the product to be void.

### Dimensions


Product Code	A	B	Cutout
SKU 22335	230	75	198

All units are in millimetres.



<p><b>Figure 1</b></p>  <p>Turn off the power</p>	<p><b>Figure 2</b></p>  <p>Drill a suitable mounting hole on ceiling according to size requirement of different item</p>
<p><b>Figure 3</b></p>  <p>Use dip switch to select desired color temperature</p>	<p><b>Figure 4</b></p>  <p>Connect input end of LED converter to commercial power(220V-240V), and make sure connecting way is right</p>
<p><b>Figure 5</b></p>  <p>Put LED driver at suitable place on ceiling</p>	<p><b>Figure 6</b></p>  <p>Pinch both springs, then push light into installation hole, hangers rebound and chuck automatically. Make sure the light fixed well.</p>

**Figure 7**



Double-check everything is well-connected, and then turn on the power

## Cleaning

Warning: Before cleaning, disconnect from mains supply and allow luminaire to cool.



## Disposal

Ensure correct disposal of this product (waste electrical and electronic equipment).

## Safety Tips

- Always ensure the power is OFF and the fitting has cooled down before performing any maintenance, cleaning, changing the globe or making any adjustment to the fitting.
- To avoid injury or damage to the fitting, ensure that power leads and screws are secure before connecting the power.
- The fitting must not be used if the protective shield has been cracked. Replace any cracked protective shield.
- Ensure that the fitting does not come in contact with corrosive chemicals etc.
- To clean, wipe with a damp clean cloth. Never soak the fitting with water.
- Do not disassemble or remold the product at will to avoid accident of electric shock or light falling.
- Input wire should use 2 \* 0.75 was H03VVH2, open the terminal cover, connected wires, forcibly pressure into the line pressing cover, ensure the line pressing cap to the end.

## Corrosion Protection

It is important to note that care must be taken during installation or maintenance to ensure that the surface of the luminaire is not damaged. Any damage, which is exposed to moisture will result in corrosion occurring.

Please also note that any chemical applications on the luminaire or chemical contact via installation will cause corrosion of the surface of the luminaire and will void the warranty.

## Warranty

- This light fitting is covered by 6 years warranty.
- If the fitting is not installed by a licensed electrician the warranty will be void.
- Please retain proof of purchase and evidence of installation by a licensed electrician for any warranty claims.
- Warranty will be void if there is any damage due to improper usage or modification to the fitting.
- Failure to comply with the instructions in this manual may increase the risk of damage or injury and will void the warranty.